

# 21301 - F102D/827/4P

GE 2D® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse









## **CAUTIONS & WARNINGS**

#### Caution

- Lamp may shatter and cause injury if broken
- Remove and install by grasping only plastic portion of the lamp.

### **GENERAL CHARACTERISTICS**

Lamp Type Compact Fluorescent - Plug-In Bulb T4

Base GR10q-4
Equivalent Wattage (NOM) 40.0 W
Rated Life (NOM) 10000.0 h
Starting Temperature (MIN) -4.0 °C
Mercury Content (NOM) 3.0 mg
Picograms of Mercury (NOM) 550.4587 pg
Primary Application Facilities;Retail

Display; Hospitality; Office; Restaurant; Warner, 1987

### PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM) 650.0 Mean Lumens (NOM) 545.0 Nominal Initial Lumens per Watt (NOM) 65.0

Color Temperature (NOM) 2700.0 K Color Rendering Index (CRI) 82.0

(NOM)

## **ELECTRICAL CHARACTERISTICS**

Wattage (NOM) 10.0
Voltage (NOM) 120.0
Current (max) (NOM) 5.25 A
Open Circuit Voltage Across 198.0 V

Starter (MIN)

Preheat Voltage (MIN) 4.25 V
Current Crest Factor (MAX) 1.7
Supply Current Frequency 20.0 Hz
(NOM)

### **DIMENSIONS**

Maximum Overall Length 3.700 in(94.0 mm)

(MOL) (NOM)

Nominal Length (NOM) 3.600 in(91.4 mm) Base Face to Top of Lamp 1.360 in(34.5 mm)

(NOM)

# **PRODUCT INFORMATION**

Product Code 21301 Description F102D/827/4P

Standard Package Case

Standard Package GTIN 00043168213011

Standard Package Quantity 60
Sales Unit Unit
No Of Items Per Sales Unit 1
No Of Items Per Standard 60

Package

UPC 043168980371

## NOTES

- 10-watt, 16-watt and 28-watt 2D lamps may be operated in any position. 21-watt, 38-watt, 39-watt, and 55-watt 2D lamps must be used with the leg market (a) in the diagram below the bend (b), in order to avoid overheating the end of the cap marked (c).
- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- Based on 60Hz reference circuit.
- Fluorescent lamp lumens decline during life