

45748 - F17T8/SP41/ECO GE Ecolux® Starcoat® T8

• Passes TCLP, which can lower disposal costs.

GENERAL CHARACTERISTICS

Lamp Type

Bulb Base Rated Life (NOM) Rated Life (instant start) @ Time Rated Life (rapid start) @ Time **Bulb Material**

Starting Temperature (MIN) Mercury Content (NOM) Picograms of Mercury (NOM) Additional Info **Primary Application**

Linear Fluorescent - Straight Linear T8 Medium Bi-Pin (G13) 30000.0 h 15000 h @ 3 h 20000 h @ 12 h 30000.0 @ 3.0/36000.0 @ 12.0 h Soda lime 10.0 °C 2.95 mg 78.04233 pg TCLP compliant Full Wattage

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM) 1325.0 Mean Lumens (NOM) 1260.0 Nominal Initial Lumens per Watt 77.94118 (NOM) Color Temperature (NOM) 4100.0 K Color Rendering Index (CRI) 78.0 (NOM) S/P Ratio (Scotopic/Photopic 1.6 Ratio) (NOM)

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	17.0
Open Circuit Voltage (rapid	285.0 V
start) (MAX)	
Open Circuit Voltage (rapid	210 V @ 10 °C
start) Min @ Temperature	
Cathode Resistance Ratio - Rh/	4.25
Rc (MIN)	
Cathode Resistance Ratio - Rh/	6.5
Rc (MAX)	
Current Crest Factor (MAX)	1.7

DIMENSIONS

Maximum Overall Length	23.780 in(604.0 mm)
(MOL) (NOM)	00 070 · (004 0)
Minimum Overall Length (NOM)	23.670 in(601.2 mm)
Nominal Length (NOM)	24.000 in(609.6 mm)
Bulb Diameter (DIA) (MIN)	0.940 in(23.9 mm)
Bulb Diameter (DIA) (MAX)	1.100 in(27.9 mm)
Bulb Diameter (DIA) (NOM)	1.000 in(25.4 mm)
Max Base Face to Base Face	23.220 in(589.8 mm)
(A) (NOM)	
Face to End of Opposing Pin	23.400 in(594.4 mm)
(B) (MIN)	
Face to End of Opposing Pin	23.500 in(596.9 mm)
(B) (MAX)	
End of Base Pin to End of	23.670 in(601.2 mm)
Opposite Pin End (C) (NOM)	. ,

PRODUCT INFORMATION

Product Code 45748 Description ANSI Code 1001-1 Standard Package Case Standard Package GTIN Standard Package Quantity 24 Sales Unit Unit No Of Items Per Sales Unit 1 No Of Items Per Standard 24 Package UPC 043168457484

F17T8/SP41/ECO 10043168457481

Rendering

Photo Not Available High Color

Photo

Not Available

CAUTIONS & WARNINGS

Caution

- · Lamp may shatter and cause injury if broken
- Wear safety glasses and gloves when handling lamp. - Do not use excessive force when installing lamp.

Warning

- Risk of Electric Shock
- Turn power off before inspection, installation or removal.

GRAPHS & CHARTS

Graphs_Spectral Power Distribution

Photo Not Available

Graphs_Lumen Maintenance

Photo Not Available

Graphs_Lamp Mortality

Photo Not Available