





GE
Lighting

16106 - FLE9/2/CAM/827

GE energy smart® CFL 9 watt blunt tip 1-pack

- \$20 in energy savings over the life of the bulb based on 3 hours per day usage
- Blunt Tip candle with medium base for use in chandeliers and sconces
- Energy Star Qualified
- Estimated yearly energy costs \$1.08 based on 3 hours per day \$0.11 per kWh
- Lasts 5.5 years based on 3 hours per day usage
- 40 watt replacement uses only 9 watts
- The GE energy smart® globe CFLs feature a GE Spiral® bulb on the inside that uses 75% less energy and lasts up to 5 times longer than incandescent decorative candles. GE energy smart® decorative bulb's shape compliments fixtures where the bulb is visible, like sconces and chandeliers

a product of
ecomagination



GENERAL CHARACTERISTICS

Lamp Type	Compact Fluorescent - Self-Ballasted
Bulb	B13
Base	Medium Screw (E26)
Equivalent Wattage (NOM)	30.0 W
Rated Life (NOM)	6000.0 h
Starting Temperature (MIN)	-15.0 °C
Total Harmonic Distortion (THD) (NOM)	125.0 %
Mercury Content (NOM)	3.5 mg
Picograms of Mercury (NOM)	1695.7 pg
Primary Application	Chandelier;Facilities;Retail Display;Hospitality;Office;Restaurant

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	430.0
Mean Lumens (NOM)	344.0
Nominal Initial Lumens per Watt (NOM)	47.77778
Color Temperature (NOM)	2700.0 K
Color Rendering Index (CRI) (NOM)	82.0

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	9.0
Voltage (NOM)	120.0
Input Voltage (NOM)	120.0 V
Input Current (NOM)	0.12 A
Power Factor (NOM)	0.6

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	5.400 in(137.2 mm)
Nominal Length (NOM)	5.400 in(137.2 mm)

PRODUCT INFORMATION

Product Code	16106
Description	FLE9/2/CAM/827
Standard Package	Case
Standard Package GTIN	10043168161067
Standard Package Quantity	10
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	10
UPC	043168161060

CAUTIONS & WARNINGS

Warning

- Risk of Electric Shock
 - Do not open - no user serviceable parts inside.
 - Do not use where directly exposed to water or outdoors without an enclosed fixture.

NOTES

- Fluorescent lamp lumens decline during life
- Lumens on one piece self ballasted lamp systems are measured base up.
- Use only on 120V 60 Hz circuits. Do not use on dimming circuits, photocells or timers. Do not use in wet locations.