



Product Number: 47659

Order Abbreviation: LU1000/SUPER5-KIT

General Description: 120/208/240/277/480V 5-tap magnetic core and coil ballast for 1000W high pressure sodium lamp

*** Full Case Required**

Product Information

Abbrev. With Packaging Info.	LU1000SUPER5KIT 1/CS 1/SKU
ANSI Code	S52
Circuit Type	CWA
Nominal Voltage (V)	120/208/240/277/480V
Number of Lamps	1
Open Circuit Voltage (V)	440
Power Factor	>0.9
Primary Lamp Type	LU1000
Sound Rating	N
Starting Method	PULSE IGNITOR
Starting Temperature - Fahrenheit	-40°F
Starting Temperature - Celsius	-40°C
Total Harmonic Distortion (THD)	<20%
Wiring Method	LEADS
Total Maximum Wattage	1100



Footnotes

- Product is a kit containing the core & coil, capacitor, ingitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- High Voltage Pulse Present on Open Circuit
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum Starting Temperature: -40F/-40C.
- Product contains installation instructions