



GE  
Lighting

## 16767 - 40BFM/H/CD2

### GE halogen 40 watt blunt tip 2-pack

- GE halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room. Plus, these bulbs last longer than regular incandescent bulbs. GE halogen decorative bulb's shape compliments fixtures where the bulb is visible, like sconces and chandeliers
- Edison™ halogen bulbs provide a brighter, crisper light that makes your home look its best
- That's why professionals choose Edison for exceptional results and longer bulb life.
- Showcase the beauty of your home with the highest quality of light.
- Blunt Tip candle with medium base for use in chandeliers and sconces
- Estimated yearly energy costs \$4.82 based on 3 hours per day \$0.11 per kWh
- Lasts 2.1 years based on 3 hours per day usage

Photo  
Not Available

Photo  
Not Available



### GENERAL CHARACTERISTICS

Lamp Type	Halogen - Decorative
Bulb	F15
Base	Medium Screw (E26)
Filament	CC-8
Rated Life (NOM)	2250.0 h
Primary Application	Chandelier

### PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	485.0
Color Temperature (NOM)	2800.0 K
Nominal Initial Lumens per Watt (NOM)	12.125

### ELECTRICAL CHARACTERISTICS

Wattage (NOM)	40.0
Voltage (NOM)	120.0

### DIMENSIONS

Maximum Overall Length (MOL) (NOM)	3.940 in(100.1 mm)
Bulb Diameter (DIA) (NOM)	1.875 in(47.6 mm)
Light Center Length (LCL) (NOM)	2.215 in(56.3 mm)

### PRODUCT INFORMATION

Product Code	16767
Description	40BFM/H/CD2
Standard Package	Case
Standard Package GTIN	10043168167670
Standard Package Quantity	5
Sales Unit	Unit
No Of Items Per Sales Unit	2
No Of Items Per Standard Package	10
UPC	043168167673

### CAUTIONS & WARNINGS

#### Caution

- Lamp may shatter and cause injury if broken
  - Dispose of lamp in a closed container.
  - Do not use lamp if outer glass is scratched or broken.

#### Warning

- Risk of Burn
  - Allow lamp to cool before handling.
- A damaged lamp emits UV radiation which may cause eye/skin injury
  - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
  - Do not exceed rated voltage.
  - Do not use lamp if outer glass is scratched or broken, even if bulb continues to light. Turn power off, remove and dispose.
- Risk of Electric Shock
  - Turn power off before inspection, installation or removal.
  - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Risk of Fire
  - In table lamp, use only with shade.
  - Keep combustible materials away from lamp.
  - Use in fixture rated for this product.

\*Eighteen month life based on rated life at 4 hours/day.