

45757 - F25T8/SPX41/ECO

GE Ecolux® Starcoat® T8 • Passes TCLP, which can lower disposal costs.

GENERAL CHARACTERISTICS

Lamp Type

Bulb Base Rated Life (NOM) Rated Life (instant start) @ Time Rated Life (rapid start) @ Time

Bulb Material Starting Temperature (MIN) Mercury Content (NOM) Picograms of Mercury (NOM) Additional Info Primary Application Linear Fluorescent - Straight Linear T8 Medium Bi-Pin (G13) 30000.0 h 15000 h @ 3 h 20000 h @ 12 h 30000.0 @ 3.0/36000.0 @ 12.0 h Soda lime 10.0 °C 2.95 mg 48.20261 pg TCLP compliant Full Wattage

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)2150.0Mean Lumens (NOM)2040.0Nominal Initial Lumens per Watt86.0(NOM)4100.0 KColor Temperature (NOM)4100.0 KColor Rendering Index (CRI)85.0(NOM)S/P Ratio (Scotopic/Photopic1.8Ratio) (NOM)1.8

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	25.0
Open Circuit Voltage (rapid	355.0 V
start) (MAX)	
Open Circuit Voltage (rapid	260 V @ 10 °C
start) Min @ Temperature	
Cathode Resistance Ratio - Rh/	4.25
Rc (MIN)	
Cathode Resistance Ratio - Rh/	6.5
Rc (MAX)	
Current Crest Factor (MAX)	1.7

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	36.000 in(914.4 mm)
Minimum Overall Length (NOM)	35.670 in(906.0 mm)
Nominal Length (NOM)	36.000 in(914.4 mm)
Bulb Diameter (DIA) (MIN)	0.940 in(23.9 mm)
Bulb Diameter (DIA) (MAX)	1.100 in(27.9 mm)
Bulb Diameter (DIA) (NOM)	1.000 in(25.4 mm)
Outside Bulb Diameter (MIN)	35.670 in(906.0 mm)
Max Base Face to Base Face	35.220 in(894.6 mm)
(A) (NOM)	
Face to End of Opposing Pin	35.400 in(899.2 mm)
(B) (MIN)	
Face to End of Opposing Pin	35.500 in(901.7 mm)
(B) (MAX)	
End of Base Pin to End of	35.670 in(906.0 mm)
Opposite Pin End (C) (NOM)	

PRODUCT INFORMATION

Product Code Description ANSI Code Standard Package Standard Package GTIN Standard Package Quantity Sales Unit No Of Items Per Sales Unit No Of Items Per Standard Package UPC 45757 F25T8/SPX41/ECO 1002-1 Case 10043168457573 24 Unit 1 24

043168457576

Photo Not Available

Rendering

Photo Not Available High Color

Photo Photo Not Available Not Available

CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
- Wear safety glasses and gloves when handling lamp.
- Do not use excessive force when installing lamp.

Warning

- Risk of Electric Shock
- Turn power off before inspection, installation or removal.

GRAPHS & CHARTS

Graphs_Spectral Power Distribution

Photo Not Available

Graphs_Lumen Maintenance

Photo Not Available

Graphs_Lamp Mortality

Photo Not Available