

# 72136 - F25T8XLSPX30WMEC

GE Ecolux® Watt-Miser® Starcoat® T8


- Passes TCLP, which can lower disposal costs.
- Provides significantly longer life than standard lamp helping to reduce maintenance costs
- Saves \$33.00 in energy costs\*











#### **GENERAL CHARACTERISTICS**

Lamp Type

Bulb Base Rated Life (NOM) Rated Life (instant start) @ Time Rated Life (rapid start) @ Time

Bulb Material Starting Temperature (MIN) Mercury Content (NOM) Picograms of Mercury (NOM) Additional Info Primary Application Linear Fluorescent - Straight Linear T8 Medium Bi-Pin (G13) 45000.0 h 24000 h @ 3 h 34000 h @ 12 h 45000.0 @ 3.0/50000.0 @ 12.0 h Soda lime 15.0 °C 2.95 mg 40.74586 pg TCLP compliant Energy Saving

# **PHOTOMETRIC CHARACTERISTICS**

Initial Lumens (NOM)1925.0Mean Lumens (NOM)1810.0Nominal Initial Lumens per Watt87.5(NOM)3000.0 KColor Temperature (NOM)3000.0 KColor Rendering Index (CRI)85.0(NOM)S/P Ratio (Scotopic/Photopic1.3Ratio) (NOM)1.3

### **ELECTRICAL CHARACTERISTICS**

Wattage (NOM)	22.0
Cathode Resistance Ratio - Rh/	4.25
Rc (MIN)	
Cathode Resistance Ratio - Rh/	6.5
Rc (MAX)	
Lamp Current (NOM)	275.0 mA
Current Crest Factor (MAX)	1.7


# DIMENSIONS

Maximum Overall Length 35.780 in(908.8 mm) (MOL) (NOM) Minimum Overall Length (NOM) 35.670 in(906.0 mm) Nominal Length (NOM) 36.000 in(914.4 mm) Bulb Diameter (DIA) (MIN) 0.940 in(23.9 mm) Bulb Diameter (DIA) (MAX) 1.100 in(27.9 mm) Bulb Diameter (DIA) (NOM) 1.000 in(25.4 mm) Outside Bulb Diameter (MIN) 35.670 in(906.0 mm) Max Base Face to Base Face 35.220 in(894.6 mm) (A) (NOM) Face to End of Opposing Pin 35.400 in(899.2 mm) (B) (MIN) Face to End of Opposing Pin 35.500 in(901.7 mm) (B) (MAX) End of Base Pin to End of 35.670 in(906.0 mm) Opposite Pin End (C) (NOM)

## **PRODUCT INFORMATION**

Product Code Description ANSI Code Standard Package Standard Package GTIN Standard Package Quantity Sales Unit No Of Items Per Sales Unit No Of Items Per Standard Package UPC 72136 F25T8XLSPX30WMEC 1002-1 Case 10043168721360 24 Unit 1 24

043168721363



### **CAUTIONS & WARNINGS**

#### Caution

• Lamp may shatter and cause injury if broken

- Wear safety glasses and gloves when handling lamp.

- Do not use excessive force when installing lamp.

- Lamp may shatter and cause injury if broken
- Wear safety glasses and gloves when handling lamp.Do not use excessive force when installing lamp.

Warning

Risk of Electric Shock


- Turn power off before inspection, installation or removal.

Risk of Electric Shock

- Turn power off before inspection, installation or removal.

# **GRAPHS & CHARTS**







# Graphs\_Lumen Maintenance

