




GE
Lighting

24699 - 30/100-HALOGEN

GE halogen 3-way 30/70/100 watt A21 1-pack

• GE halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room. GE halogen 3-way bulbs provide three levels of light for maximum flexibility--low for mood lighting and energy savings, high for task lighting. Plus, these bulbs last longer than regular incandescent bulbs. Use GE halogen 3-way bulbs in table lamps and floor lamps with 3-way sockets and showcase the beauty of your home

- A21 shape with medium base for use in table lamps and enclosed fixtures
- Estimated yearly energy costs \$3.61/\$8.43/\$12.05 based on 3 hours per day \$0.11 per kWh
- Lasts 2.3 years based on 3 hours per day usage



GENERAL CHARACTERISTICS

Lamp Type	Halogen - A-line
Bulb	A21
Base	3 Contact Medium Screw (E26D)
Filament	CC-8
Rated Life (NOM)	2500.0 h
Life in Years (NOM)	2.3
Primary Application	3-Way

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	300.0 /1050.0 /1350.0 /320.0 /1370.0
Color Temperature (NOM)	2900.0 K
Nominal Initial Lumens per Watt (NOM)	13.5 /15.0 /10.0

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	30.0
Voltage (NOM)	120.0
Estimated Energy Cost per Year (NOM)	3.61

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	5.250 in(133.4 mm)
Bulb Diameter (DIA) (NOM)	2.625 in(66.7 mm)

PRODUCT INFORMATION

Product Code	24699
Description	30/100-HALOGEN
Standard Package	Case
Standard Package GTIN	10043168246993
Standard Package Quantity	6
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	6
UPC	043168246996

CAUTIONS & WARNINGS

Caution

- Risk of Burn
 - Allow lamp to cool before handling.
- Lamp may shatter and cause injury if broken
 - Dispose of lamp in a closed container.
 - Do not use lamp if outer glass is scratched or broken.

Warning

- Risk of Fire
 - Keep combustible materials away from lamp.
 - Use in fixture rated for this product.
 - Use in fixture rated for this product--see instructions.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
 - Do not exceed rated voltage.
 - Do not use lamp if outer glass is scratched or broken, even if bulb continues to light. Turn power off, remove and dispose.
- Risk of Electric Shock
 - Turn power off before inspection, installation or removal.