




GE
Lighting

10042 - 100BTT/SW/CD

GE Edison™ BT14.5

- Edison™ halogen bulbs provide a brighter, crisper light that makes your home look its best
- That's why professionals choose Edison for exceptional results and longer bulb life.
- Showcase the beauty of your home with the highest quality of light.



GENERAL CHARACTERISTICS

Lamp Type	Halogen - A-line
Bulb	BT14.5
Base	Medium Screw (E26)
Filament	C-8
Rated Life (NOM)	3000.0 h
Primary Application	Standard

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	1600.0
Color Temperature (NOM)	2900.0 K
Nominal Initial Lumens per Watt (NOM)	16.0

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	100.0
Voltage (NOM)	120.0

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	4.750 in(120.6 mm)
Light Center Length (LCL) (NOM)	3.000 in(76.2 mm)

PRODUCT INFORMATION

Product Code	10042
Description	100BTT/SW/CD
Standard Package	Case
Standard Package GTIN	10043168100424
Standard Package Quantity	5
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard	5
Package	
UPC	043168100427

CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
 - Dispose of lamp in a closed container.
 - Do not use lamp if outer glass is scratched or broken.

Warning

- Risk of Burn
 - Allow lamp to cool before handling.
- A damaged lamp emits UV radiation which may cause eye/skin injury
 - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
 - Do not exceed rated voltage.
 - Do not use lamp if outer glass is scratched or broken, even if bulb continues to light. Turn power off, remove and dispose.
- Risk of Electric Shock
 - Turn power off before inspection, installation or removal.
 - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Risk of Fire
 - In table lamp, use only with shade.
 - Keep combustible materials away from lamp.
 - Use in fixture rated for this product.

*Guaranteed to last 2 years based on 4 hours use per day at 120V.