

**Product** 18359**Number:****Order** 25T8N 120V**Abbreviation:****General** Incandescent T8 Bulb Shape Home Appliance Light Clear**Description:** Finish Intermediate Base 25Watt 120Volt

Product Information

Abbrev. With Packaging Info.	25T8N 120V 60/CS 10/SKU
Approx. Lumens	230
Average Rated Life (hr)	1000
Base	Intermediate
Bulb	T8
Class	B (vacuum)
Color Rendering Index (CRI)	100
Color Temperature/CCT (K)	2850
Diameter (in)	1.000
Diameter (mm)	25.40
Filament	C-7A
Lamp Finish	Clear
Light Center Length - LCL (in)	1.313
Light Center Length - LCL (mm)	33
Maximum Overall Length - MOL (in)	2.625
Maximum Overall Length - MOL (mm)	66.675
Nominal Voltage (V)	120.00
Nominal Wattage (W)	25.00

Footnotes

- Average laboratory life is 200 hours for vacuum cleaner and 600 hours for sewing machine services.