




GE  
Lighting

## 20641 - 35PAR16CURIO

### GE energy-efficient halogen 35 watt PAR16 floodlight 1-pack

- Edison™ halogen bulbs provide a brighter, crisper light that makes your home look its best
- That's why professionals choose Edison for exceptional results and longer bulb life.
- Showcase the beauty of your home with the highest quality of light.
- Estimated yearly energy costs \$4.22 based on 3 hours per day \$0.11 per kWh
- GE energy-efficient halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room. These GE energy-efficient halogen floodlights use less energy than standard halogen bulbs, saving money on energy. GE energy-efficient halogen floodlights feature lenses designed to provide a precise beam pattern, dispensing broad beams of crisp, white light throughout your home's interior. Use these bulbs in indoor track and recessed fixtures instead of regular incandescent and create a dramatic effect
- Lasts 2.7 years based on 3 hours per day usage
- PAR16 indoor floodlight with medium base for use in directional fixtures such as recessed can lighting



### GENERAL CHARACTERISTICS

Lamp Type	Halogen - MR
Bulb	JDR16
Base	Medium Screw (E26)
Filament	CC-6V
Rated Life (NOM)	3000.0 h
Primary Application	Curio Cabinet

### PHOTOMETRIC CHARACTERISTICS

Center Beam Candlepower (CBCP) (NOM)	500.0
Color Temperature (NOM)	2700.0 K

### ELECTRICAL CHARACTERISTICS

Wattage (NOM)	35.0
Voltage (NOM)	120.0

### DIMENSIONS

Maximum Overall Length (MOL) (NOM)	2.047 in(52.0 mm)
Bulb Diameter (DIA) (NOM)	2.000 in(50.8 mm)

### PRODUCT INFORMATION

Product Code	20641
Description	35PAR16CURIO
Standard Package	Case
Standard Package GTIN	10043168206416
Standard Package Quantity	3
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	3
UPC	043168206419

### CAUTIONS & WARNINGS

#### Caution

- Lamp may shatter and cause injury if broken
  - Dispose of lamp in a closed container.
  - Do not use lamp if outer glass is scratched or broken.

#### Warning

- Risk of Burn
  - Allow lamp to cool before handling.
- Risk of Electric Shock
  - Turn power off before inspection, installation or removal.
- A damaged lamp emits UV radiation which may cause eye/skin injury
  - Turn power off if glass bulb is broken. Remove and dispose of lamp.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
  - Do not exceed rated voltage.
  - Do not use lamp if outer glass is scratched or broken.
- Risk of Fire
  - In table lamp, use only with shade.
  - Keep combustible materials away from lamp.
  - Use in fixture rated for this product.

\*Two year life based on rated life at 4 hours/day.