

**Product** 16159**Number:****Order** 39PAR30LN/HAL/SP10 130V 10/CS**Abbreviation:****General** Tungsten Halogen PAR30LN Reflector Lamp 39Watt 130Volt**Description:** Medium Base Spot10 Beam**\* Full Case Required****Product Information**

|                                   |                                   |
|-----------------------------------|-----------------------------------|
| Abbrev. With Packaging Info.      | 39PAR30LNHALSP10 130V 10/CS 1/SKU |
| Approx. Lumens                    | 550                               |
| Average Rated Life (hr)           | 1500                              |
| Base                              | E26 Medium                        |
| Beam Angle (deg)                  | 10                                |
| Beam Type                         | SP                                |
| Bulb                              | PAR30LN                           |
| Centerbeam Candlepower (cp)       | 6100                              |
| Class                             | C (gas)                           |
| Color Rendering Index (CRI)       | 100                               |
| Color Temperature/CCT (K)         | 2850                              |
| Diameter (in)                     | 3.752                             |
| Diameter (mm)                     | 95.30                             |
| Ecologic                          | Yes                               |
| Family Brand Name                 | Halogen Par30 Long Neck           |
| Filament                          | CC-8                              |
| Horizontal Beam Angle (deg)       | 10                                |
| Lamp Finish                       | Reflector                         |
| Maximum Overall Length - MOL (in) | 4.625                             |
| Maximum Overall Length - MOL (mm) | 119.0625                          |
| Nominal Voltage (V)               | 130.00                            |
| Nominal Wattage (W)               | 39.00                             |
| Vertical Beam Angle (deg)         | 10                                |

**Footnotes**

- State of the Art SPL Optics
- For indoor or outdoor use where not directly exposed to weather. Exposure to weather may damage the bulb.
- In base up operation, heat may eventually deteriorate paper-lined or plastic sockets.