



GE
Lighting

16753 - Q20GU10/FL/CD

GE halogen 20 watt MR16 1-pack

- Edison™ halogen bulbs provide a brighter, crisper light that makes your home look its best
- That's why professionals choose Edison for exceptional results and longer bulb life.
- Showcase the beauty of your home with the highest quality of light.
- Estimated yearly energy costs \$2.41 based on 3 hours per day \$0.11 per kWh
- Estimated yearly energy costs \$2.41 based on 3 hours per day \$0.11 per kWh
- Lasts 1.8 years based on 3 hours per day usage
- MR16 shape with GU10 base for use directional fixtures such as recessed can lighting
- Input Voltage = 120 volts
- GE halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room or interior space. Use GE halogen GU10 bulbs in indoor track and recessed lighting and create a dramatic effect



GENERAL CHARACTERISTICS

Lamp Type	Halogen - MR
Bulb	MR16
Base	GU10
Filament	CC-2V
Rated Life (NOM)	2000.0 h
Primary Application	Indoor Floodlight

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	80.0
Center Beam Candlepower (CBCP) (NOM)	230.0
Color Temperature (NOM)	2600.0 K
Beam Spread (NOM)	25.0 °

ELECTRICAL CHARACTERISTICS



Wattage (NOM)	20.0
Voltage (NOM)	120.0

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	2.125 in(54.0 mm)
Bulb Diameter (DIA) (NOM)	2.000 in(50.8 mm)

PRODUCT INFORMATION

Product Code	16753
Description	Q20GU10/FL/CD
Standard Package	Case
Standard Package GTIN	10043168167533
Standard Package Quantity	5
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard	5
Package	
UPC	043168167536



CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
 - Dispose of lamp in a closed container.
 - Do not use lamp if outer glass is scratched or broken.

Warning

- Risk of Burn
 - Allow lamp to cool before handling.
- Risk of Electric Shock
 - Turn power off before inspection, installation or removal.
- A damaged lamp emits UV radiation which may cause eye/skin injury
 - Turn power off if glass bulb is broken. Remove and dispose of lamp.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
 - Do not exceed rated voltage.
 - Do not use lamp if outer glass is scratched or broken.
- Risk of Fire
 - In table lamp, use only with shade.
 - Keep combustible materials away from lamp.
 - Use in fixture rated for this product.

*Two year life based on rated life at 4 hours/day.