

DOWN LIGHTING SERIES

5&6 INCH 12W Ra80

Greenlux LED



DL5612DIM128027K
DL5612DIM128030K
DL5612DIM128040K
DL5612DIM128050K



12W REPLACE



100W

Halogen

80% Energy Savings

PRO

\$440 Energy Saving Per Lamp*

1000
LM
BRIGHTNESS

DIMMABLE

83
LPW
EFFICACY

5
YR
WARRANTY

80
CRI(Ra)

50,000
H

- ★ Low energy consumption
- ★ Efficient LED replacement for halogen bulbs
- ★ Improved color Rendering
- ★ No UV radiation
- ★ Especially suitable for public areas like lobbies
- ★ Suitable for commercial and residential lighting

CLASSIFIED
UL US
E476291




lighting
facts
LED Product Partner

LM 79

LM 80



- ★ We use innovative, specially designed reflector and PC cover to optimize beam distribution.
- ★ This reflector and PC cover create soft, pleasant light, with low glare.
- ★ The reflector and PC cover design provides high luminescence with an even beam pattern.



- ★ Unique heat sink design.
- ★ Seamless aluminum and structure design to reduce the operating temperature of the LED chips.
- ★ Excellent heat sink guarantees a longer life.
- ★ The size-adjusted design can make the size switched freely between 5" & 6" in the actual application.

ATR Lighting

10 Industrial Rd Richland, MO 65556

Toll Free: (800) 624-4568 Local: (573) 765-5219 Fax: (800) 747-0999

DOWN LIGHTING SERIES 5&6 INCH 12W Ra80

Greenlux LED

GENERAL LIGHTING





RECESSED LIGHTING



ACCENT LIGHTING



ILLUMINANCE



SPECIFICATION

Product Model DL5612DIM128027K DL5612DIM128030K DL5612DIM128040K DL5612DIM128050K

Type	Down Light5&6	Down Light5&6	Down Light5&6	Down Light5&6
SKU#	8000817	8000824	8000831	8000848
Base	E26/GU24	E26/GU24	E26/GU24	E26/GU24
Power(W)	12W	12W	12W	12W
Voltage-Frequency	120V 60Hz	120V 60Hz	120V 60Hz	120V 60Hz
Color Temperature	Soft White 2700K	Warm White 3000K	Cool White 4000K	Daylight 5000K
Ra	>80	>80	>80	>80
Typical Lumen(lm)	1000lm	1000lm	1000lm	1000lm
Efficacy	83	83	83	83
Beam Angle	100°	100°	100°	80°
Dimmable	YES	YES	YES	YES
Power Factor	>0.9	>0.9	>0.9	>0.9
Life time	50000H	50000H	50000H	50000H
Replace	100W	100W	100W	100W