



GE  
Lighting

## 11117 - 50PAR30L/H/SP10

GE energy-efficient halogen 50/46 watt PAR30 longneck spotlight 1-pack

• GE energy-efficient halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room. These GE energy-efficient halogen spotlights use less energy than standard halogen bulbs, saving money on energy. GE energy-efficient halogen spotlights feature lenses designed to provide a precise beam pattern, dispensing narrow beams of crisp, white light perfect for spotlighting artwork and architectural details. Use these bulbs in indoor track and recessed fixtures instead of regular incandescent and create a dramatic effect

- Standard Halogen - Crisp, white light
- Estimated yearly energy costs \$6.02 based on 3 hours per day \$0.11 per kWh
- Lasts 2.7 years based on 3 hours per day usage
- PAR30 longneck indoor spotlight with medium base for use in directional fixtures such as recessed can lighting



### GENERAL CHARACTERISTICS

Lamp Type	Halogen - PAR
Bulb	PAR30L
Base	Medium NP
Filament	CC-8
Rated Life (NOM)	3000.0/6000.0 h

### PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	580.0 /460.0
Center Beam Candlepower (CBCP) (NOM)	7500.0
Color Temperature (NOM)	2800.0 K
Beam Spread (NOM)	10.0 °
Nominal Initial Lumens per Watt (NOM)	11.6 /10.0

### ELECTRICAL CHARACTERISTICS

Wattage (NOM)	50.0
Voltage (NOM)	130.0
Burn Position	Universal burning position

### DIMENSIONS

Maximum Overall Length (MOL) (NOM)	4.750 in(120.6 mm)
Bulb Diameter (DIA) (NOM)	3.750 in(95.2 mm)

### PRODUCT INFORMATION

Product Code	11117
Description	50PAR30L/H/SP10
Standard Package	Case
Standard Package GTIN	10043168111178
Standard Package Quantity	15
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	15
UPC	043168111171

### CAUTIONS & WARNINGS

#### Caution

- Lamp may shatter and cause injury if broken
  - Do not use lamp if outer glass is scratched or broken.

#### Warning

- Risk of Burn
  - Allow lamp to cool before handling.
- Risk of Fire
  - Keep combustible materials away from lamp.
- Risk of Electric Shock
  - Turn power off before inspection, installation or removal.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
  - Do not use lamp if outer glass is scratched or broken.
  - Do not use where directly exposed to water or outdoors without an enclosed fixture.